

Smart efficient power anywhere.

Lightweight and portable inverter generators for travel and recreational activities.





Added benefits



Quieter*

Consistent, quiet power that traditional camping generators can't match



Dime



Inverter technology Produces smoother power

for sensitive electronics



Powersmart mode

Automatically adjusts engine speed to save fuel and run longer



Series	P2400 PowerSmart™ Series
Model #	030802
Running Watts ¹	1800
Starting Watts ²	2400
Phase/Voltage	1PH/230
Engine	
CC	79
Outlets	
	2 x 230V, 15A
	1 x 12V, 5A - Regulated
	2 x USB
ensions (L x W x H)	50.9 cm x 31.1 cm x 44.1 cm

3 Years Consumer 1 Year Commercial

Weight 22.7 kg

Limited Warranty⁴

Features	
Fuel Tank Capacity	3.8 Litres
Decibel Rating (25% load/Rated load) ³	58/65
Alternator	Permanent Magnet
Starting	Pull Start
Low Oil Shutdown	✓
Protected Outlet Covers	✓
Automatic Idle Control	✓
Muffler (Spark Arrester Type)	Standard
Hour Meter	-
Fuel Gauge	-
LCD StatStation™	-
Wheels	-



Series	P3400 PowerSmart™ Series
Model #	030808
Running Watts ¹	2800
Starting Watts ²	3400
Phase/Voltage	1PH/230
Engine	
CC	171
Outlets	
	2 x 230V, 15A
	1 x 12V, 5A - Regulated
	1 x USB
Dimensions (L x W x H)	66 cm x 35.2 cm x 51.7 cm
Weight	38.6 kg
Limited Warranty⁴	3 Years Consumer 1 Year Commercial

Features	
Fuel Tank Capacity	5.7 Litres
Decibel Rating (25% load/Rated load) ³	58/67
Alternator	Permanent Magnet
Starting	Pull Start
Low Oil Shutdown	✓
Protected Outlet Covers	✓
Automatic Idle Control	✓
Muffler (Spark Arrester Type)	Standard
Hour Meter	✓
Fuel Gauge	✓
LCD StatStation™	✓
Wheels	6"

Features Fuel Tank Capacity 13.2 Litres

Low Oil Shutdown Protected Outlet Covers Automatic Idle Control Muffler (Spark Arrester Type) Standard

> Fuel Gauge InfoHub Wheels 6"

Alternator Permanent Magnet Starting Electric / Pull Start

Hour Meter Via mobile app InfoHub™

Decibel Rating (25% load/Rated load)3 61





Series	P4500 PowerSmart™ Series
Model #	030807
Running Watts ¹	3700
Starting Watts ²	4500
Phase/Voltage	1PH/230
Engine	
CC	224
Outlets	
	2 x 230V, 15A
	1 x 12V, 5A - Regulated
	2 x USB
nsions (L x W x H)	62.2cm x 44.7cm x 51.6cm
Weight	47 kg
_imited Warranty ⁴	3 Years Consumer 1 Year Commercial







Commercial Limited



¹ Per CSA C22.2 No. 100-14.

² Starting Watts reflects the maximum current that can momentarily be supplied when starting a motor, multiplied by the generator's rated voltage.

 $^{\scriptscriptstyle 3}$ At 7m from control panel side.

⁴ See www.briggsandstratton.com for warranty details.

Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. Product may vary from images shown.