



# EU32i

## Leisure and Commercial Generator

4-Stroke

### UNIT

<b>Engine Type</b>	GX130
<b>Fuel Tank Capacity</b>	4.6 Litres as per SM
<b>Continuous Operating Hours</b>	3.3 hr @ rated load 8.5 hr @ 1/4 load
<b>LwA Sound Power (at 4m)</b>	91dB(A) <sup>D4</sup>

### POWER

<b>Max. AC Output power factor 1.0</b>	3200VA
<b>Rated AC Output</b>	2600VA
<b>DC Rated Output for Charging Automotive Batteries Only</b>	-

### MEASUREMENTS

<b>Electric Starter</b>	No
<b>Inverter Technology</b>	Yes
<b>Voltmeter</b>	No
<b>AC Circuit Protector</b>	Yes
<b>DC Circuit Protector</b>	No
<b>Pilot Lamp</b>	Yes
<b>On-Board Fuel Gauge</b>	Yes
<b>Oil Alert</b>	Yes
<b>Auto Throttle</b>	Eco-Throttle™
<b>Auto Choke</b>	Fuel Injected
<b>Large Capacity Fuel Tank</b>	13L
<b>4 Year Domestic Warranty*</b>	Yes
<b>Bluetooth®<sup>D2</sup></b>	Yes

### MEASUREMENTS

<b>LxWxH (mm)</b>	571 x 306 x 452
<b>Dry Weight</b>	26.5kg