

# P3400

- ✓ COGuard - Shuts down your generator when harmful levels of carbon monoxide are detected
- ✓ QPT™ Quiet Power Technology - Automatically adjusts the engine speed further reducing noise and fuel consumption
- ✓ Easy Portability with 2-person H-Beam Carry Handle
- ✓ The PowerSmart Series Inverter Generators deliver 'pure sine waves' at 3400 watts peak and 2800 watts continuous making it ideal for sensitive electronic equipment



<b>Running</b>	2.8 kW / 3.5kVA
<b>Starting</b>	3.4 kW / 4.25kVA
<b>Engine</b>	Briggs & Stratton
<b>Displacement</b>	171cc
<b>Voltage</b>	230V
<b>Amperage</b>	15A
<b>Start Type</b>	Recoil
<b>Fuel Tank Capacity</b>	5.7L
<b>Handle</b>	Front Telescopic handle
<b>Outlets</b>	2 x 15A, 1 x 12V 5A DC charging, 2 x USB ports
<b>Noise Level</b>	58 dBA @ 7m
<b>Dimensions</b>	660(L) x 352(W) x 517(H)mm
<b>Weight</b>	38.6kg